

NEC TABLE 250.102(C)(1): BONDING JUMPER SIZING

SERVICE CONDUCTOR SIZE (CU)	SERVICE CONDUCTOR SIZE (AL)	BONDING JUMPER (CU)	BONDING JUMPER (AL)
2 or smaller	1/0 or smaller	8	6
1 or 1/0	2/0 or 3/0	6	4
2/0 or 3/0	4/0 or 250 kcmil	4	2
Over 3/0 - 350	Over 250 - 500	2	1/0
Over 350 - 600	Over 500 - 900	1/0	3/0
Over 600 - 1100	Over 900 - 1750	2/0	4/0
Over 1100	Over 1750	12.5% of Phase Area	12.5% of Phase Area



TECHNICAL REFERENCE DATA

PRO GRADE DOCUMENTATION



ONLINE ELECTRICAL TOOLS

<https://zing2.app>

VISIT ZING2.APP FOR FULL TABLE